



GTS **NEOCELL**[®]

HMC55-H

A Charging Holster for Motorola[®]
MC55/MC65 Handheld Computers

■ Introduction

- **Lasts up to longer.** The Holster continuously charges Motorola[®] MC55/MC65's internal battery so it stays powered longer, helping to improve productivity.
- **Reduces costs and clutter.** The all-in-one design of the Holster eliminates the need for separate chargers. Simply charge the Holster with its own power cord (included).
- **Clearly indicates status.** LED lights on the Holster tell you whether it's fully charged.
- **Device Face-out Orientation.** Allow user to keep working while charging the device.
- **RAM Mount Compatibility.** Back Adapter makes HMC55-H holster compatible with RAM Mount
- **Works the way you do.** The Holster's ergonomic shape makes it easy to wear and easy to grip. Plus, its facedown design protects the screen.

■ Equipment Supplied

- One (1) HMC55-H Charging Holster
- One (1) AC:DC power supply with integrated line cord
- One (1) Operations Manual

■ Product Specifications

Device Supported:	Motorola® MC55/MC65 Series Handheld Computer
Holster Battery Capacity:	4000 mAh
Operating Temperature:	Charging 0°C to +40°C (+32°F to +104°F) Discharging -20°C to +50°C (-4°F to +122°F)
Storage Range:	-20°C to +50°C (-4°F to +122°F)
Dimensions:	Height: 168 mm Width: 90 mm Thickness: 58 mm (Without device inserted) Weight: 333 g
Power Supply Voltages:	AC: 100-240V, 50/60Hz Input DC: 5.4 V/3A Max Output
Charge Time:	With Device - Up to 8 hrs maximum (With device LCD screen off or under power saving mode) (varies with battery capacity) Without Device - Up to 5 hrs maximum
Charge Current:	Up to 1500 mA in Constant Current Charge phase

* Note that specifications may change at any time.

■ Operation

1. Holster Operation:
 - Insert One of Motorola® MC55/MC65 series device to the Holster.
 - Holster provides external power to the device automatically.
 - Please refer to device user manual for LED indication.
2. Charge Holster:
 - Insert power supply to Holster DC jack.
 - The Holster LED turns Red while charging.
 - The Holster LED turns to Green when the Holster is fully charged.
 - User can keep the device in the Holster while charging.
 - With the device engaged to the Holster, the device will be charged first.
 - To have best charging efficiency, it is strongly recommended to let device turn off automatically when charging.
 - As for the functions of device LED, please refer to the device user manual.
3. Mini USB Port:
 - Mini USB port is designed to provide the user with a communication function between the Holster and Motorola® MC55/MC65 Series device to download and upload data.

LED Indicator

When the Holster power is low, LED starts flashing in Red to warn users to charge the Holster.

LED Indicator (with External Power Supply)	Solid Red	Charging in progress
	Solid Green	Holster battery is fully charged.
LED Indicator (without External Power Supply)	Flash Red	Holster battery power is low. Remove the device from the Holster and charge the Holster immediately.

Safety Guidelines & Warnings

- Before using this Holster, please read all instructions and cautionary notations on the Holster, on the battery to be charged, and on the host device.
- To reduce risk of injury, only use authorized battery products with Holster. Other non-approved batteries may cause personal injury and / or damage to the equipment.
- Do not expose the Holster to excessive moisture, temperature extremes or direct sunlight.
- To reduce risk of electric shock, unplug the Holster from power source before cleaning.
- Dispose of used batteries in accordance with your state or local hazardous material laws.
- Dispose of device correctly according to local regulations to comply with WEEE regulations.
- Do not disassemble, incinerate, modify, or short circuit the charger, any battery, or related components.



Troubleshooting

If the Holster does not operate after you have followed the previous operating instructions, then please try the following:

- Check the system power at the AC outlet if you cannot charge the Holster.
- Check for loose cable connections if you cannot charge the Holster.
- Check to insure the device is properly inserted into the Holster slot.
- Check to insure the device is functioning properly.

CAUTION

Do not pour, spray or spill any liquid into or onto the Holster. If liquid does come into contact with the Holster, immediately un-plug the Holster and remove any device.

■ Warranty & Support

Global Technology Systems, Inc. products are designed to be compliant with the rules and regulations in the localities in which the products are sold and will be labeled as required. The limits are designed to provide reasonable protection against harmful interference when electronic devices are operated in a commercial environment.

For warranty and service information call 1-508-650-1172. Outside North America, please contact your local Global Technology Systems representative.

Each charger is guaranteed to be free from defects in materials and workmanship for 24 months from date of shipment under normal use.

The charger must remain unmodified and must be operated under normal and proper conditions. The warranty is limited to repair or replacement at Global Technology System, Inc., with reasonable promptness after being returned and received by Global Technology System, Inc. These provisions do not extend the original warranty term for any product or device which was repaired or replaced. This warranty applies to the original owner and does not extend to any product or device which was subject to misuse, neglect, accidental damage, unauthorized repair or tampering. Preventive maintenance activities are not covered by this warranty.



■ For additional information or replacement parts, please contact:

Global Technology Systems, Inc.
550 Cochituate Road
Framingham, MA 01701 USA
In the US 1-800-267-2711
www.GTSpower.com